

BLMA

26 ... 40 GHz

EMI Preamplifier

Standard Models

Model	Frequency Range	Output Power P _N min dBm	Gain min / typ dB	Noise Figure dB	Dimensions (W,H,D) mm	Weight kg
BLMA 2640-M	26 ... 40 GHz	+5	38 / 42 ±4	2.7	93 x 65 x 206	1
BLMA 2640-1A	26 ... 40 GHz	+6	20 / 22 ±2	4.5	93 x 65 x 206	1
BLMA 2640-3A	26 ... 40 GHz	+10	30 / 32 ±2	4.0	93 x 65 x 206	1
BLMA 2640-4A	26 ... 40 GHz	+10	40 / 42 ±2	4.0	93 x 65 x 206	1
BLMA 2640-5A	26 ... 40 GHz	+10	50 / 52 ±2	4.0	93 x 65 x 206	1

Standard Specifications:

Output Impedance:	50 Ohm nominal
Load VSWR:	<2,5:1 typ.
Spurious:	-50 dBc typ. (excluding harmonics)
Harmonics:	-20 dBc min.
Class of Operation:	A-linear

General:

RF Input:	precision N-m (<18 GHz) horn antenna (>18 GHz)
RF Output:	precision N-f (<18 GHz) K-f (>18 GHz)
Mains Supply:	85 ... 264 V AC / 47 ... 63 Hz Option L: 230 V AC / 47 ... 63 Hz
Power Consumption:	<10 W

BONN Elektronik GmbH – BLMA 26 ... 40 GHz

Conformity:	CE (EN 55022, CISPR 22)
Ambient Temperature:	0 ... +45 °C
Storage Temperature:	-20 ... +85 °C
Relative Humidity:	up to 95% (non-condensing)
Operating Altitude:	up to 2000 m above sea level
Vibration and Shock:	MIL-STD-810 F
Mounting:	via HF 906 horn antenna (<18 GHz) mounting bracket for mounting to tripods (>18 GHz)

Options:

-A: CISPR, FCC, MIL, EN	for basic laboratory measurements (economic)
-1A: CISPR, FCC, MIL, EN	for civil applications
-M: MIL-461, MIL-285	for MIL-compliant measurements
-BT: Bluetooth	for measurements of bluetooth systems (including filter)
(1)	The Bluetooth filter limits the useable frequency range to 3 ... 18 GHz!

H) Battery Operation

L) Linear regulated power supply

Specifications are subject to change without notice

BONN Elektronik GmbH – BLMA 26 ... 40 GHz



Rudolf-Diesel-Str.18 · D-85521 Ottobrunn · Tel +49 (0)89/608 754-0 · Fax +49 (0)89/608 754-99
email: info@bonn-elektronik.com · home: www.bonn-elektronik.com